

# ANALOGUE METERS



## PHASE SEQUENCE INDICATOR SQ 0201 AND TEMPERATURE METERS

A **phase sequence indicator** is intended for determining phase sequences in a three-phase network, from 100 V to 500 V and from 50 Hz to 60 Hz.

The indicator is provided with two built-in glow lamps which indicate L1, L2, L3 phase sequence.

**Temperature meters** are intended for connection to various thermocouples or temperature dependant resistors with the possibility of analogue output. The accuracy class is 1.5.



SQ 0201



KQ 0x07

TYPE		KQ 0307	KQ 0307	KQ 0207	KQ 0207
Front frame (mm)		72 x 72	72 x 72	96 x 96	96 x 96
Cutting for mounting (mm)		68 x 68	68 x 68	92 x 92	92 x 92
Scale length (mm)		65	65	95	95
ANALOGUE OUTPUT		-	0...10 mA Rmax=200Ω	-	0...10 mA Rmax=200Ω
<b>MEASURING RANGE</b>					
Resistor probe Pt 100	+/-50°C	•	•	•	•
	0...100°C	•	•	•	•
	0...200°C	•	•	•	•
	0...300°C	•	•	•	•
	0...400°C	•	•	•	•
Thermocouple J Fe-CuNi	0...200°C	•	•	•	•
	0...400°C	•	•	•	•
	0...600°C	•	•	•	•
Thermocouple K NiCr-Ni	0...600°C	•	•	•	•
	0...800°C	•	•	•	•
	0...1200°C	•	•	•	•
Thermocouple S PtRh-Pt	0...1400°C	•	•	•	•
	0...1600°C	•	•	•	•

Supply: 230V~ +/-10% (50...60 Hz)  
On request: KQ 0207, KQ 0307  
110V~ +/-10% (50...60 Hz)

Other thermocouples on request.  
Dimensional drawings on pages 143, 144.